

B.E., DEGREE EXAMINATIONS: NOV/DEC 2012

Fifth Semester

MECHATRONICS ENGINEERING

MCT109: Control Systems

(Semi log graphs, polar graph sheet & ordinary graph sheets are to be supplied)

Time: Three Hours**Maximum Marks: 100****Answer all the Questions:-****PART A (10 x 1 = 10 Marks)**

- In a field controlled DC servomotor, the armature is supplied by -----
 - Constant current
 - Constant voltage
 - Constant field flux
 - Both a & b
- The force balance equation of an ideal spring element is -----
 - $F = B \frac{dx}{dt}$
 - $F = K \frac{dx}{dt}$
 - $F = Kx$
 - $F = K \frac{\partial x}{\partial t}$
- Mass is having ----- relationship with natural frequency of 2nd order mechanical systems
 - inversely proportional
 - proportional
 - exponential
 - bimodal
- If the damping ratio of a system is 0.75 and the natural frequency of oscillation is 12 rad/sec then what will be the peak overshoot
 - 2.6%
 - 2.8%
 - 3%
 - 2.4%
- The expression of resonant peak of a second order system is given by
 - $M_r = \frac{1}{2\zeta\sqrt{1-\zeta^2}}$
 - $M_r = \frac{\zeta}{2\sqrt{1-\zeta}}$
 - $M_r = \frac{1}{\zeta\sqrt{1-\zeta^2}}$
 - $M_r = \frac{1}{2\zeta\sqrt{1-\zeta}}$
- The corner frequency of a transfer function $\frac{1}{s}$ is ----
 - 8 rad/sec
 - 1 Hz
 - 1 rad/sec
 - none
- A system with single root at origin is
 - oscillatory
 - unstable
 - stable
 - marginally stable

- b) Convert the block diagram shown in Figure 2 to signal flow graph and find the transfer function using Mason's gain formula.




Figure 2

22. a) Derive the following time domain specifications for a second order system:
- (i) Rise time (7)
- (ii) Peak time (7)

(OR)

- b) There are different process stations available in a petrochemical industry. The process stations are needed to be precisely controlled to manufacture different by-products from the crude oil. To manufacture naphtha from crude oil, the process station should be a unity feedback control system with an open loop transfer function of $G(s) = 10/s(s+2)$. If the input flow of crude oil to the station increased by a step of 12 units then what will be the rise time, percentage of overshoot and peak time of this process station. Assume the system is a linear one.

23. a) Obtain gain and phase cross over frequencies using bode plot for a transfer function $G(s) = \frac{10}{s(1+0.4s)(1+0.1s)}$

(OR)

- b) Consider a unity feedback system having an open loop transfer function $G(s) = \frac{K}{s(1+0.2s)(1+0.05s)}$. Sketch the polar plot and determine the K value so that (i) gain margin is 18dB (ii) phase margin is 60° .

24. a) Check the stability of a system, whose characteristic equation is governed by $s^6 + s^5 + 3s^4 + 3s^3 + 3s^2 + 2s + 1 = 0$, use Routh Hurwitz method

(OR)

- b) Sketch a root locus of a unity feedback control system having an open loop transfer function $G(s) = \frac{K}{s(s^2+4s+13)}$.

25. a) A unity feedback control system has open loop transfer function $G(s) = \frac{K}{s(0.1s+1)(0.2s+1)}$. The system is required to satisfy the following performance specifications: 1) $K_v = 30$ 2) Phase margin $\geq 40^\circ$ 3) bandwidth $\omega_b = 5$ rad/sec. Choose a suitable compensation technique and justify why it was selected.

(OR)

- b) Consider a type 1 unity feedback system with an open loop transfer function $G(s) = k/s(s+1)$. It is desired to have the velocity error constant $K_v = 10$. Furthermore, phase margin of the system to be at least 45° . Design compensator using Bode plot.
