



B.E DEGREE EXAMINATIONS: MAY 2018

(Regulation 2015)

Sixth Semester

MECHATRONICS ENGINEERING

U15MCT601: Microcontroller and Embedded Systems

COURSE OUTCOMES

- CO1:** Differentiate microcontroller from microprocessor and explain the general architecture of microcontrollers
- CO2:** Explain the applications of micro controllers and differentiate few microcontroller cores based on their construction and applications
- CO3:** Summarize the memory organization and internal communication of 8051 and PIC micro controller.
- CO4:** Program, 8051 using different addressing modes and effectively use the timers, counters and interrupts for a given application
- CO5:** Describe the architecture of real time operating systems with inter task communication
- CO6:** Design embedded system scheme for few real time domestic, auto and space applications

Time: Three Hours

Maximum Marks: 100

Answer all the Questions:-

PART A (10 x 1 = 10 Marks)

1. Matching type item with multiple choice code

CO1 [K₂]

List I	List II
A. SoC	i. Logic Analyzer
B. Monitoring	ii. RISC
C. Harvard architecture	iii. Fourth generation
D. Embedded System	iv. ARM

- | | A | B | C | D |
|----|-----|----|-----|----|
| a) | ii | i | iii | iv |
| b) | iii | iv | ii | i |
| c) | ii | iv | iii | i |
| d) | iii | i | ii | iv |

2. Which of the following in one-time programmable memory?

CO3 [K₂]

- | | |
|----------|----------|
| a) SRAM | b) PROM |
| c) FLASH | d) NVRAM |

3. The following features are applicable to 8051 microcontroller: CO3 [K₂]
1. Word length is 16 bits.
 2. Harvard architecture.
 3. Signed arithmetic operations.
 4. A/D conversion available on chip.
- a) 1,3 b) 1,4
c) 1,2 d) 2,3
4. When using serial communication in 8051 at a baud rate of 4800, the following number has to be loaded in TH1: CO4 [K₂]
- a) -6 b) +6
c) FA d) -FA
5. Assertion (A): Timers of 8051 can be alternatively used as counters. CO2 [K₂]
Reason (R): Counters count external pulses.
- a) Both A and R are Individually true and R is the correct explanation of A b) Both A and R are Individually true but R is not the correct explanation of A
c) A is true but R is false d) A is false but R is true
6. The register that allows the PIC microcontroller memory space to be expanded from 2K to 8K is: CO3 [K₂]
- a) Program Counter b) RP0
c) INDF d) PCLATH
7. The following sequence of instructions generates nested delay in PIC microcontroller: CO4 [K₃]
LOOP
1. decfsz COUNTL, F
 2. decfsz COUNTH, F
 3. goto LOOP
 4. goto LOOP
 5. return
- a) 2-3-4-1 b) 1-3-2-4
c) 3-4-2-1 d) 4-1-3-2
8. The part of RTOS that keeps track of each task and its state is CO5 [K₂]
- a) Kernel b) Task manager
c) Scheduler d) ISR

9. Assertion (A): Reset of an embedded system generates a non-maskable interrupt. CO5 [K₂]
Reason (R): Reset stabilizes the embedded system.
- a) Both A and R are Individually true and R is the correct explanation of A b) Both A and R are Individually true but R is not the correct explanation of A
c) A is true but R is false d) A is false but R is true
10. The system that maintains the speed of a car constant is CO6 [K₂]
a) Embedded system b) Cruise control
c) Real-time control d) 8051 microcontroller

PART B (10 x 2 = 20 Marks)
(Answer not more than 40 words)

11. Differentiate between Little-Endian and Big-Endian controllers. CO1 [K₂]
12. Express the number 436_d in packed and unpacked BCD format, assuming byte sized memory. CO2 [K₂]
13. Which bits in which registers must be set to give serial data interrupt the highest priority? CO3 [K₂]
14. Write 8051 instructions that send the ASCII code for A on Port 0 and ASCII code for B on Port 1. CO4 [K₃]
15. Move the data 42H from accumulator to memory location 42H using indirect addressing. CO4 [K₃]
16. What is instruction pipelining? CO3 [K₂]
17. What is the function of watchdog timer in PIC microcontroller? CO3 [K₂]
18. Enumerate the three states in which a task in RTOS can exist. CO5 [K₂]
19. How do pointers and queue facilitate interface to RTOS? CO5 [K₂]
20. What is ABS? CO6 [K₂]

Answer any FIVE Questions:-
PART C (5 x 14 = 70 Marks)
(Answer not more than 300 words)

Q.No. 21 is Compulsory

21. i) Describe the architecture of 8051 microcontroller with neat block diagram. (10) CO1 [K₂]
ii) Enumerate the characteristic features of 8051. (4)
22. i) Explain the different classification of embedded systems with an example each. (10) CO2 [K₂]
ii) Enumerate any four application areas of embedded systems. (4)
23. With a neat schematic, explain how program and data memory (internal and external) is interfaced to 8051 microcontroller. CO3 [K₃]

24. i) Write an assembly language program to generate a square wave of frequency 1 kHz (10) CO4 [K₃]
on P1.2 continuously. Assume clock frequency of 11.0592 MHz.
ii) Explain the four addressing modes of 8051 with an example each. (4) [K₂]
25. Explain the architecture and peripherals of PIC microcontroller with necessary diagrams. CO3 [K₂]
26. i) Describe how semaphores are used by RTOS to take care of shared data problems. (10) CO5 [K₂]
ii) Write a note on handheld operating systems. (4)
27. Explain how an automatic washing machine is designed using an embedded system. CO6 [K₃]
