



B.E DEGREE EXAMINATIONS: DEC 2022

(Regulation 2018)

Third Semester

ELECTRONICS AND COMMUNICATION ENGINEERING

U18ECT3004: Electromagnetic Fields

COURSE OUTCOMES

- CO1:** Describe the fundamental concepts of static electric field (K2).
CO2: Explain the fundamental concepts of static magnetic field (K2).
CO3: Solve electrostatic and magneto static boundary problems (K3).
CO4: Analyze the effect of static electric and magnetic fields under various configurations (K4).
CO5: Analyze the significance of Maxwell's equations for time varying field (K4).
CO6: Apply Maxwell's equations to analyze wave propagation in various mediums (K3).

Time: Three Hours

Maximum Marks: 100

Answer all the Questions:-

PART A (10 x 1 = 10 Marks)

1. Match List I with List II

CO1 [K₂]

List I	List II
A. Electric field intensity due to an infinite sheet charge	i. $\oint A \cdot dl = \int (\nabla X A) \cdot ds$
B. Coulomb's law	ii. $\oint D \cdot ds = Q_{encl}$
C. Stokes' theorem	iii. $\frac{Q_1 Q_2}{4\pi\epsilon_0 R^2} \overline{a_R}$
D. Gauss's law	iv. $\frac{\rho_s}{2\epsilon_0} \overline{a_N}$

- | | A | B | C | D |
|----|-----|-----|-----|----|
| a) | ii | i | iii | iv |
| b) | iii | iv | ii | i |
| c) | iv | iii | i | ii |
| d) | iii | i | ii | iv |

2. The electric field intensity at a point situated 4 m from a point charge is 200 N/C. If the distance is reduced to 2 m, the field intensity will be -----

CO1 [K₂]

- | | |
|------------|-------------|
| a) 400 N/C | b) 800 N/C |
| c) 600 N/C | d) 1200 N/C |

3. Which of the following statements are correct? CO4 [K₂]
1. The thinner the dielectric, the more the capacitance.
 2. Capacitance increases with increase in plate area & decrease in distance between the plates.
 3. Capacitance increases with decrease in plate area and value of applied voltage.
 4. In a capacitor the electric charge is stored in metal plates.
- a) 1,2,3 b) 1,3,4
c) 1,2,4 d) 2,3,4
4. The Lorentz force equation is given by ----- CO2 [K₂]
- a) $F=Q(E-v.B)$ b) $F=Q(E+v.B)$
c) $F=Q(E-v \times B)$ d) $F=Q(E+v \times B)$
5. Assertion (A): No Magnetic flux exists in a closed surface. CO2 [K₂]
Reason (R) : Number of magnetic field lines leaving the surface is equal to the number of field lines entering the surface
- a) Both A and R are Individually true and R is the correct explanation of A b) Both A and R are Individually true but R is not the correct explanation of A
c) A is true but R is false d) A is false but R is true
6. Which of the following is correct? CO4 [K₂]
- 1) $W_H = \frac{1}{2} LI$ 2) $W_H = \frac{1}{2} LI^2$ 3) $W_H = \frac{1}{2} L/I^2$ 4) $W_E = \frac{1}{2} CV^2$
- a) 1,2 b) 2,4
c) 3,4 d) 1,4
7. In magnetic boundary conditions, ----- and -----are continuous. CO3 [K₂]
- a) $H_{\text{tangential}}, B_{\text{tangential}}$ b) $H_{\text{normal}}, B_{\text{tangential}}$
c) $H_{\text{normal}}, B_{\text{normal}}$ d) $H_{\text{tangential}}, B_{\text{normal}}$
8. The phase constant of a dielectric with frequency 3×10^6 rad/sec in free space is ----- CO6 [K₃]
- a) 1.0 b) 0.01
c) 0.1 d) 0.001
9. Assertion (A): In a lossy dielectric medium, depth of penetration of a plane wave increases with decreasing frequency. CO6 [K₂]
Reason (R): The rate of attenuation is very high in lossy dielectric medium.
- a) Both A and R are Individually true and R is the correct explanation of A b) Both A and R are Individually true but R is not the correct explanation of A
c) A is true but R is false d) A is false but R is true
10. The magnitude of average poynting vector of the electromagnetic wave with electric and magnetic field intensities given by 4 v/m and 8 A/m respectively is ----- W/m² CO5 [K₃]

- b) Formulate the expression for continuity equation for current. 6 CO4 [K₃]
24. a) Elaborate the boundary conditions for electric field when a wave travels between two different dielectric medium. 8 CO3 [K₂]
- b) Differentiate between self and mutual inductance. Coil 1 of a pair of coupled coils has a continuous current of 5A, and the corresponding fluxes ϕ_1 and ϕ_{12} are 0.6mWb and 0.4 mWb respectively. If the turns are $N_1=500$ and $N_2=1500$, find L_1 , L_2 , and M . 6 CO4 [K₃]
25. a) From the basic laws derive the time varying Maxwell's equation and explain the significance of each equation in details. 10 CO5 [K₃]
- b) For a lossy dielectric $\sigma = 5$ s/m, $\epsilon_r = 1$ and $E = 100 \sin 3t$. Find J_C and J_D . 4 CO5 [K₃]
26. a) Using Maxwell's equations, derive the electromagnetic wave equations for a conducting medium. 8 CO6 [K₂]
- b) If a uniform plane wave is travelling in a lossy dielectric which is having ϵ_r of 2.5, μ_r of 4, σ of 10^{-3} mho/m at 10 MHz, then evaluate its attenuation constant, phase constant and velocity. 6 CO6 [K₃]
