

B.E DEGREE EXAMINATIONS: APRIL /MAY 2024

(Regulation 2018)

Fourth Semester

ELECTRONICS AND COMMUNICATION ENGINEERING

U18ECT4104: Transmission Lines and Waveguides

Smith Chart to be Provided

COURSE OUTCOMES

- CO1: Discuss the fundamental concepts of wave propagation in Transmission Lines and Wave Guides.
- CO2: Analyze the line parameters and various losses in transmission lines.
- CO3: Apply smith chart for line parameter and impedance calculations.
- CO4: Evaluate the characteristics of Parallel plane and Rectangular wave guides.
- CO5: Evaluate the characteristics of Circular wave guides and Rectangular cavity resonators.

Time: Three Hours**Maximum Marks: 100****Answer all the Questions:-****PART A (10 x 2 = 20 Marks)****(Answer not more than 40 words)**

1. A line operated at 1.6 GHz has parameters of $L=0.002\mu\text{H/m}$, $C=0.012\text{pF/m}$, $R=0.015\ \Omega/\text{m}$ and $G=0.1\text{mS/m}$, Find Z, Y and Z_0 . CO1 [K₃]
2. State the conditions for the distortion less line. CO1 [K₂]
3. List the assumptions for the analysis of the performance of the radio frequency line. CO2 [K₂]
4. Define Reflection factor and Reflection loss. CO2 [K₂]
5. Give reasons for preferring a short- circuited stub when compared to an open –circuited stub. CO3 [K₂]
6. Compare single stub with double stub matching. CO2 [K₃]
7. Give the reason for impossibility of TEM waves in waveguides. CO4 [K₃]
8. Find the cutoff frequency of an air-filled rectangular waveguide with dimensions of 8x4 cm for TE₁₀ mode. CO4 [K₃]
9. Define quality factor of a resonator. CO5 [K₂]
10. A circular waveguide operated at 11GHz has an internal diameter of 4.5 cm. For a TE₁₀ mode propagation calculate λ and λ_c . CO5 [K₃]

Answer any FIVE Questions:-
PART B (5 x 16 = 80 Marks)
(Answer not more than 400 words)

11. Derive the general solution for voltage and current at any point on a line in two standard forms and explain its physical significance. 16 CO1 [K2]
12. a) Discuss the types of waveform distortion on a transmission line and obtain the condition for distortion less line. 10 CO2 [K3]
- b) A transmission line has the following parameters $L=0.1 \mu\text{H}$, $R=5\Omega$, $C=300\text{pF}$, $G=0.01 \text{ mho}$. Find γ , Z_0 of a line at 500 MHz 6 CO2 [K3]
13. A slotted line measurement of a transmission line with a characteristic impedance of 60Ω indicates a VSWR of 4.0 and the location of the first voltage minima of the standing wave pattern to be 0.1λ from the load. Assuming $d_1=0.05 \lambda$ and $d_2=0.375 \lambda$ and using the Smith chart find the lengths of the two stubs to achieve a match between the line and the load. 16 CO3 [K4]
14. a) Derive the components of electric and magnetic field strength between a pair of perfectly conducting planes of infinite extent in Y and Z directions. The planes are separated in X direction by 'a' meter. 12 CO4 [K3]
- b) For a frequency of 5GHz and plane separation of 4cm for TM_{10} mode, find cutoff frequency and cutoff wavelength. 4 CO4 [K3]
15. a) Obtain the solution for electric and magnetic field components of TE waves along rectangular waveguide 12 CO4 [K3]
- b) In TE_{10} mode of wave propagation in a rectangular waveguide, if the broader dimension of the waveguide is 40 cm, find the cutoff wavelength for that mode. 4 CO4 [K3]
16. Derive the unloaded quality factor of a rectangular cavity resonator (a x b x d) excited in TE_{101} mode for $d>a>b$. What is the condition for maximum Q? 16 CO5 [K3]
